

Product Picture	Description	Dimension
Pilot Lamp LAS0-K-D/△/▲/※	LED color △ RGBYBW LED voltage ▲ 6V / 12V / 24V / 110V / 220V / 380V IP degree※ P:IP65 / No letter means IP40 Accessory Protective cover T16	
Transparent Ring Pilot Lamp LAS0-K-EA/△/▲/※	LED color △ RGBYBW LED voltage ▲ 6V / 12V / 24V / 110V / 220V / 380V IP degree※ P:IP65 / No letter means IP40 Accessory Protective cover T16	
Ring Pilot Lamp LAS0-K-EB/△/▲/※	LED color △ RGBYBW LED voltage ▲ 6V / 12V / 24V / 110V / 220V / 380V IP degree※ P:IP65 / No letter means IP40 Accessory Protective cover T16	
Push button (can be illuminated) MR-LAS0-K-□■/△/▲/※	Contact □ 11: 1NO1NC / 10: 1NO / 01: 1NC Other switch combinations refer to the model description Operation ■ Z: Latching / No letter: Momentary LED color △ RGBYBW LED voltage ▲ 6V / 12V / 24V / 110V / 220V IP degree※ P:IP65 / No letter means IP40 Accessory Protective cap T16 / T35 protective cover	
Push button (can be illuminated) MR-LAS0-K-□■EA/△/▲/※	Contact □ 11: 1NO1NC / 10: 1NO / 01: 1NC Other switch combinations refer to the model description Operation ■ Z: Latching / No letter: Momentary LED color △ RGBYBW LED voltage ▲ 6V / 12V / 24V / 110V / 220V IP degree※ P:IP65 / No letter means IP40 Accessory Protective cap T16 / T35 protective cover	

PART NUMBERS ON THIS DRAWING
MR-LAS0-K MR-LAS0-K-D MR-LAS0-K-EA MR-LAS0-K-EA-PB MR-LAS0-K-EB MR-LAS0-K-EB-PB
MR-LAS0-K-MA MR-LAS0-K-MB MR-LAS0-K-P MR-LAS0-K-Q MR-LAS0-K-S MR-LAS0-K-TSA
MR-LAS0-K-TSB MR-LAS0-K-TSC MR-LAS0-K-X MR-LAS0-K-XA MR-LAS0-K-XB MR-LAS0-K-XD
MR-LAS0-K-YA MR-LAS0-K-YTS

22 MM PUSH BUTTON MR-LAS0-K SERIES		Micro-Ray	
PART NO	MR-LAS0-K		
DWG NO	MR-LAS0-K	SHEET 1 OF 4	REV A
UNITS: mm	SCALE: NTS - DO NOT SCALE	SIZE A4	DATE 2026-09-22

Product Picture	Description	Dimension
Ring Push button (can be illuminated) MR-LAS0-K-□■EB/△/▲/※	Contact □ 11: 1NO1NC / 10: 1NO / 01: 1NC Other switch combinations refer to the model description Operation ■ Z: Latching / No letter: Momentary LED color △ R G Y B W LED voltage ▲ 6V / 12V / 24V / 110V / 220V / 380V IP degree ※ P:IP65 / No letter means IP40 Accessory Protective cap T16 / T35 protective cover	
Metal Flat Head Push button MR-LAS0-K-□■P/※	Contact □ 11: 1NO1NC / 10: 1NO / 01: 1NC Other switch combinations refer to the model description Operation ■ Z: Latching / No letter: Momentary IP degree ※ P:IP65 / No letter means IP40 Accessory Protective cap T16 / T35 protective cover	
Metal Domed Head Push button MR-LAS0-K-EB/△/▲/	Contact □ 11: 1NO1NC / 10: 1NO / 01: 1NC Other switch combinations refer to the model description Operation ■ Z: Latching / No letter: Momentary IP degree ※ P:IP65 / No letter means IP40 Accessory Protective cap T16 / T35 protective cover	
Selector Switch MR-LAS0-K-□X/◇◆/※	Contact □ 11: 1NO1NC / 20: 2NO / 02: 2NC Other switch combinations refer to the model description Operation ◇ ◆ (32 Default right momentary, left momentary can be customized) Contact, pls refer to "contact on/off chart" IP degree ※ P:IP65 / No letter means IP40 Accessory T35 protective cover	
A Type Lever Switch MR-LAS0-K-□XA/◇◆/※	Contact □ 11: 1NO1NC / 20: 2NO / 02: 2NC Other switch combinations refer to the model description Operation ◇ ◆ (32 Default right momentary, left momentary can be customized) Contact, pls refer to "contact on/off chart" IP degree ※ P:IP65 / No letter means IP40 Accessory T35 protective cover	

PART NUMBERS ON THIS DRAWING
MR-LAS0-K MR-LAS0-K-D MR-LAS0-K-EA MR-LAS0-K-EA-PB MR-LAS0-K-EB MR-LAS0-K-EB-PB
MR-LAS0-K-MA MR-LAS0-K-MB MR-LAS0-K-P MR-LAS0-K-Q MR-LAS0-K-S MR-LAS0-K-TSA
MR-LAS0-K-TSB MR-LAS0-K-TSC MR-LAS0-K-X MR-LAS0-K-XA MR-LAS0-K-XB MR-LAS0-K-XD
MR-LAS0-K-YA MR-LAS0-K-YTS

22 MM PUSH BUTTON MR-LAS0-K SERIES		Micro-Ray	
PART NO	MR-LAS0-K		
DWG NO	MR-LAS0-K	SHEET 2 OF 4	REV A
UNITS: mm	SCALE: NTS - DO NOT SCALE	SIZE A4	DATE 2026-09-22

Product Picture	Description	Dimension
B Type Lever Switch MR-LAS0-K-□XB/◇/△/※	Contact □ 11: 1NO1NC / 20: 2NO / 02: 2NC Other switch combinations refer to the model description Operation ◇ (32 Default right momentary, left momentary can be customized) Contact, pls refer to "contact on/off chart" LED color △ R G Y N IP degree※ P:IP65 / No letter means IP40 Accessory T35 protective cover	
D Type Selector Switch MR-LAS0-K-□XD/◇/△/※	Contact □ 11: 1NO1NC / 20: 2NO / 02: 2NC Other switch combinations refer to the model description Operation ◇ (32 Default right momentary, left momentary can be customized) Contact, pls refer to "contact on/off chart" IP degree※ P:IP65 / No letter means IP40 Accessory T35 protective cover	
Key-lock Switch MR-LAS0-K-EB/△/▲/※	Contact □ 11: 1NO1NC / 20: 2NO / 02: 2NC Other switch combinations refer to the model description Operation ◇ (32 Default right momentary, left momentary can be customized) Contact, pls refer to "contact on/off chart" Unmovable Position of Key ● Refer to Notes IP degree※ P:IP65 / No letter means IP40 Accessory T35 protective cover	
A Type Illuminated Mushroom MR-LAS0-K-□■MA/△/▲/※	Contact □ 11: 1NO1NC / 10: 1NO / 01: 1NC Other switch combinations refer to the model description Operation ■ Z: Latching / No letter: Momentary LED color △ R G LED voltage ▲ 6V / 12V / 24V / 110V / 220V IP degree※ P:IP65 / No letter means IP40 Accessory T35 protective cover/ Protective cap T16 / Protective cap T24-A	
B Type Mushroom LAS0-K-□■MB/R/※	Contact □ 11: 1NO1NC / 10: 1NO / 01: 1NC Other switch combinations refer to the model description Operation ■ Z: Latching / No letter: Momentary LED color △ R IP degree○ P:IP65 / No letter means IP40 Accessory T35 protective cover/ Protective cap T16 / Protective cap T24-A	

PART NUMBERS ON THIS DRAWING
MR-LAS0-K MR-LAS0-K-D MR-LAS0-K-EA MR-LAS0-K-EA-PB MR-LAS0-K-EB MR-LAS0-K-EB-PB
MR-LAS0-K-MA MR-LAS0-K-MB MR-LAS0-K-P MR-LAS0-K-Q MR-LAS0-K-S MR-LAS0-K-TSA
MR-LAS0-K-TSB MR-LAS0-K-TSC MR-LAS0-K-X MR-LAS0-K-XA MR-LAS0-K-XB MR-LAS0-K-XD
MR-LAS0-K-YA MR-LAS0-K-YTS

22 MM PUSH BUTTON MR-LAS0-K SERIES		Micro-Ray	
PART NO	MR-LAS0-K		
DWG NO	MR-LAS0-K	SHEET 3 OF 4	REV A
UNITS: mm	SCALE: NTS - DO NOT SCALE	SIZE A4	DATE 2026-09-22

Product Picture	Description	Dimension
A Type Emergency stop switch MR-LAS0-K-□TSA/R/※	Contact □ 11: 1NO1NC / 10: 1NO / 01: 1NC Other switch combinations refer to the model description IP degree ※ P: IP65 / No letter means IP40 Accessory T35 protective cover/ Warning ring T14-2260 / T26 protection ring	
B Type Emergency stop switch MR-LAS0-K-□TSB	Contact □ 11: 1NO1NC / 10: 1NO / 01: 1NC Other switch combinations refer to the model description IP degree IP40 Accessory T35 protective cover/ Warning ring T14-2260 / T26 protection ring	
C Type Emergency stop switch MR-LAS0-K-EB/△/▲/	Contact □ 11: 1NO1NC / 10: 1NO / 01: 1NC Other switch combinations refer to the model description IP degree ※ P: IP65 / No letter means IP40 Accessory T35 protective cover/ Warning ring T14-2260 / T26 protection ring	
Emergency stop Key-lock Switch LAS0-K-□YTS	Contact □ 11: 1NO1NC / 10: 1NO / 01: 1NC Other switch combinations refer to the model description IP degree IP40 Accessory T35 protective cover/ Warning ring T14-2260 / T26 protection ring	
Double-position (can be illuminated) MR-LAS0-K-□S/▲	Contact □ 11: 1NO1NC / 10: 1NO / 01: 1NC Other switch combinations refer to the model description LED voltage ▲ 6V / 12V / 24V / 110V / 220V IP degree IP40 Accessory T35 protective cover	

PART NUMBERS ON THIS DRAWING

MR-LAS0-K MR-LAS0-K-D MR-LAS0-K-EA MR-LAS0-K-EA-PB MR-LAS0-K-EB MR-LAS0-K-EB-PB
MR-LAS0-K-MA MR-LAS0-K-MB MR-LAS0-K-P MR-LAS0-K-Q MR-LAS0-K-S MR-LAS0-K-TSA
MR-LAS0-K-TSB MR-LAS0-K-TSC MR-LAS0-K-X MR-LAS0-K-XA MR-LAS0-K-XB MR-LAS0-K-XD
MR-LAS0-K-YA MR-LAS0-K-YTS

22 MM PUSH BUTTON		Micro-Ray	
MR-LAS0-K SERIES			
PART NO	MR-LAS0-K		
DWG NO	MR-LAS0-K	SHEET 4 OF 4	REV A
UNITS: mm	SCALE: NTS - DO NOT SCALE	SIZE A4	DATE 2026-09-22